

产品参数表 Product Specification

DW2-RF

RF无线门窗传感器/RF Wireless Door/Window Sensor



基本信息 Basic Information

| | |
|---------------------------|------------------------------|
| 产品系列 Product series | 安防系列 Smart Home Security |
| 产品类型 Type | 门/窗传感器 Door/Window Sensor |
| 工作电压 Working voltage | DC12V |
| 电池型号 Battery model | 27A 12V |
| 静态电流 Quiescent current | ≤1.5uA |
| 发射电流 Emission current | ≤20mA |
| 安装距离 Installation gap | <5mm |
| MCU | 1527+115H |
| 产品认证 Certification | CE/FCC/ROHS |

外观信息 Appearance

| | |
|-------------------------|--|
| 产品颜色 Color | 白色 White |
| 尺寸规格 Dimension | 发射器: 70x31x19mm 磁铁: 42x14x16mm Transmitter: 70x31x19mm Magnet: 42x14x16mm |
| 产品净重 Weight | 27g |
| 外壳材质 Casing material | PC V0 |

功能特性 Features

| | |
|---------------------------|--|
| 产品特点 Functions | 本设备通过将磁铁和发射器分离去触发发射器,发射器发出触发消息及时推送至APP,主要用于门窗的开启/关闭、破坏报警等。 This is a 433MHz wireless door/window sensor which triggers the transmitter by separating the magnet from the transmitter, then the transmitter will send an alarm message and pushes it to APP. It is used to trigger alert messages when the door/window is opened and closed. |
| 适配的网关 Matched gateways | SONOFF RF Bridge及其他无线协议为433MHz的网关,具体以实际产品为准。 SONOFF RF Bridge and gateways supporting 433MHz wireless protocol. Detailed information is in accordance with the final product. |

无线标准 Wireless standard

| | |
|--|----------------------------------|
| 发射频率 RF | 433.92MHz |
| 无线发射距离 Wireless transmission distance | 最大50米 Max. 50m |
| 天线 Antenna | 模块板载天线 PCB board with antenna |

使用环境 Working Environment

| | |
|-----------------------------|---|
| 适用场所 Applicable place | 室内使用 Indoor |
| 工作温度 Working temperature | -10°C ~ 40°C |
| 工作湿度 Working humidity | 5%-95% RH, 无冷凝 5%-95% RH, non-condensing |
| 工作海拔 Working height | 2000米以下 Less than 2000m |

安装信息 Installation

| | |
|-----------------------|---------------------------------------|
| 固定方式 Applicability | 通过3M胶粘贴固定 3M adhesive installation |
|-----------------------|---------------------------------------|